

*plus.audio*

# ***ET SERIES***

*Touring Sound Made Easy.*



*plus.audio*

# ET SERIES

*Touring Sound Made Easy*

The ET Series (Easytour) is a highly versatile solution ideal for rental companies' everyday needs beyond just serving as a FOH Main PA for up to 40m throw distance. This easy-to-tour system consists of 10" line array elements and matching single and dual 18" subwoofers, available in self-powered or passive options. It is an intuitive plug-and-play system that is easy to set up and transport.

---

## Easy to Use

Pole mount 2 top cabinets onto the subwoofer for optimal listening height at indoor corporate events





### Easy to Fly

Fly up to 16 cabinets in a vertical line array configuration for medium-sized outdoor festivals or venues with complex vertical coverage requirements.



### Easy to Stack

Ground stack 2 subs and 4 tops for powerful side fills or "Texas Headphones" suitable for demanding bands and DJs.

- The Easytour series feature both single 18" and dual 18" subwoofers.

## Easy to Configure

The standard configuration is a self-powered hybrid system. The powered 18" subwoofer contains an inbuilt AC1P 4-channel amplifier that can power four ET110L mid-high cabinets and an additional 18" passive subwoofer.

The AC1P utilises a Powersoft amp module and contains presets for various configurations of the Easytour system. Additional presets for other Plus Audio speakers, like the CPH212 point source or FM Series monitors, offers flexibility for use as a full range drum fill or high-powered point source system. The Easytour system can also be driven by external rack mounted amplifiers like the AC1R or AC8.



● ET218B / ET218BA



Standard Configuration  
as a self-powered  
hybrid system



## Easy to Transport

Two ET110L mid-high elements stack on top of one ET118BA Subwoofer and are secured by the fly-frame.



● FM12C Floor Monitor

● FM14C Floor Monitor

## Technical Specifications

Model	ET110L	ET118B	ET218B
<b>Frequency Response</b>	80Hz ~ 20kHz (-10dB)	35Hz ~ 150Hz (-10dB)	35Hz ~ 150Hz (-10dB)
<b>Sensitivity (1W / 1m)</b>	HF: 112dB, LF: 103dB	100dB	104dB
<b>Nominal Impedance</b>	HF: 16Ω, LF: 16Ω	4Ω	4Ω
<b>Power Rating(AES)</b>	HF: 90W, LF: 400W	800W	1600W
<b>Components</b>	1 x 10" driver with neodymium magnet	1x 18" driver with ferrite magnet	2 x 18" driver with ferrite magnet
	1 x 3 " Compression driver with neodymium	-	-
	magnets and 1.4" exit	-	-
<b>Nominal Dispersion</b>	H:90° x V:10°	-	-
<b>Maximum SPL</b>	138dB	135dB	142dB
<b>Dimensions (H x W x D)</b>	308 x 527 x 342 mm	778 x 527 x 729mm	626 x 770 x 1100 mm
<b>Weight</b>	18kg	59kg	96,5kg
<b>Connector</b>	2 x Neutrik NL4MP	1 x Neutrik NL4MP	1 x Neutrik NL4MP
<b>Connection Method</b>	LF: 1+1-, HF 2+2-	1+1-	1+1-
<b>Enclosure</b>	Multilayer birch plywood	Multilayer birch plywood	Multilayer Birch Plywood
<b>Finish</b>	Black polyurethane paint	Black polyurethane paint	Black polyurethane paint
<b>Grille</b>	Black steel grille with acoustic foam	Black steel grille with acoustic foam	Black steel grille with acoustic foam



## Technical Specifications

Model	ET118BA	ET218BA
Frequency Response	35Hz ~ 150Hz (-10dB)	35Hz ~ 150Hz (-10dB)
Sensitivity (1W / 1m)	100dB	104dB
Nominal Impedance	4Ω	4Ω
Power Rating(AES)	800W	1600W
Components	1x 18" driver with ferrite magnet	2 x 18" driver with ferrite magnet
Maximum SPL	135dB	142dB
Dimensions (H x W x D)	778 x 527 x 729mm	626 x 770 x 1100mm
Weight	65,4kg	104,4kg
Enclosure	Multilayer birch plywood	Multilayer birch plywood
Finish	Black polyurethane paint	Black polyurethane paint
Grille	Black steel grille with acoustic foam	Black steel grille with acoustic foam
Amplifier Type	Class - D	Class - D
Output Power	4x 1600W, 4Ω	4x 1600W, 4Ω
Power Supply	Universal, regulated switch mode with PFC (power factor correction)	Universal, regulated switch mode with PFC (power factor correction)
DSP	Dante enabled (optional), 64bit multimode processing, 96kHz sample rate, 2 sec delay (input),50ms (output), 2 inputs, 4 outputs.	Dante enabled (optional), 64bit multimode processing, 96kHz sample rate, 2 sec delay (input),50ms (output), 2 inputs, 4 outputs.
AD/DA	24 bit / 96 Khz	24 bit / 96 Khz
THD+N	< 0.05% (typical)	< 0.05% (typical)
SNR	115 dB (A weighted)	115 dB (A weighted)
Input/Output	2 x XLR-F Input, 2x XLR-M Link Out	2 x XLR-F Input, 2x XLR-M Link Out
Output Connectors	2x Neutrik NL4MP Full Range Output LF: 1+1-HF: 2+2- Ext / Sub Output: 1+1-	2x Neutrik NL4MP Full Range Output LF: 1+1-HF: 2+2- Ext / Sub Output: 1+1-
Socket	1x PowerCON input, 1x PowerCON output	1x PowerCON input, 1x PowerCON output
Preset	6 Factory Presets, 100 Total	6 Factory Presets, 100 Total



**Plus Audio is a Stage Audio Works Brand**

22 Kyalami Boulevard, Kyalami Park, Midrand, 1684, South Africa  
087 55 10 100 | [www.plus.audio](http://www.plus.audio)